


PRODUCT-DETAILS

CT6/2000

CT6/2000 Current transformer



General Information

Extended Product Type	CT6/2000
Product ID	2CSG421230R1101
EAN	8012542606406
Catalog Description	CT6/2000 Current transformer
Long Description	CT6/2000 is used to transform primary currents to../5A secondary currents for c.a. measurement instruments

Technical

Cable Use	Cable and Horizontal bar
Rated Primary Current (I _{pn})	2000 A
Current Limit Function	FS 5
Frequency (f)	50 ... 60 Hz
Power Loss	16 W
Secondary Output Connection	Plug-in connection
Accuracy	±0,5%
Mounting Type	Through primary
Model Number	Through-feed current converter
Cable Cross-Section	50 mm
Rated Cross-Section	60 x 20 mm

Environmental

Ambient Air Temperature	Operation -5 ... 50 °C
Degree of Protection	IP30
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment
Environmental Information	See RoHS Information

Dimensions

Product Net Width	105 mm
Product Net Height	26.5 mm
Product Net Depth / Length	61 mm
Product Net Weight	0.450 kg

Container Information

Package Level 1 Units	box 1 piece
Package Level 1 Width	0.121 m
Package Level 1 Height	0.061 m
Package Level 1 Depth / Length	0.105 m
Package Level 1 Gross Weight	1 kg
Package Level 1 EAN	8012542606406

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85043121
Country of Origin	Italy (IT)

Certificates and Declarations (Document Number)

Declaration of Conformity - CE	9AKK106713A5700
Environmental Information	See RoHS Information
Instructions and Manuals	2CSC446012B0201
RoHS Information	2CSC445004K0201

Popular Downloads

Data Sheet, Technical Information	9AKK107046A0430
Instructions and Manuals	2CSC446012B0201

Classifications

ETIM 7	EC002048 - Current transformer
ETIM 8	EC002048 - Current transformer
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer

CN8	85043121
eClass	V11.0 : 27210902
Object Classification Code	T

Categories

Low Voltage Products and Systems → Modular DIN Rail Products → Energy Efficiency Devices → Current Transformers

