

Circuit-breaker, 3p, 125A, plug-in module

Part no. **NZMN1-A125-SVE**
 Catalog No. **112762**

EL-Nummer
 (Norway) **4363475**



Powering Business Worldwide™

Similar to illustration


Delivery program

| | | | |
|--|---|--------------------------|------------|
| Product range | Circuit-breaker | | |
| Protective function | System and cable protection | | |
| Standard/Approval | IEC | | |
| Installation type | Plug-in units | | |
| Release system | Thermomagnetic release | | |
| Construction size | NZM1 | | |
| Number of poles | 3 pole | | |
| Standard equipment | Box terminal | | |
| Switching capacity | | | |
| 400/415 V 50 Hz | I_{cu} | kA | 50 |
| Rated current = rated uninterrupted current | | | |
| Rated current = rated uninterrupted current | $I_n = I_u$ | A | 125 |
| Setting range | | | |
| Overload trip |  | I_r | A |
| | | | 100 - 125 |
| Short-circuit releases |  | | |
| Non-delayed |  | $I_i = I_n \times \dots$ | 6 - 10 |
| Short-circuit releases |  | I_{rm} | A |
| | | | 750 - 1250 |

Technical data

| | | | |
|---|--|----------------------------------|--|
| General | | | |
| Standards | IEC/EN 60947 | | |
| Protection against direct contact | Finger and back of hand proof to VDE 0106 Part 100 | | |
| Climatic proofing | Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30 | | |
| Ambient temperature | | | |
| Ambient temperature, storage | $^{\circ}\text{C}$ | - 40 - + 70 | |
| Operation | $^{\circ}\text{C}$ | - 25 - + 70 | |
| Mechanical shock resistance (10 ms half-sinusoidal shock) according to IEC 60068-2-27 | g | 20 (half-sinusoidal shock 20 ms) | |
| Safe isolation to EN 61140 | | | |
| Between auxiliary contacts and main contacts | V AC | 500 | |
| between the auxiliary contacts | V AC | 300 | |
| Mounting position | Vertical and 90° in all directions | | |

| | |
|--|--|
| Direction of incoming supply | as required |
| Degree of protection | |
| Device | In the operating controls area: IP20 (basic degree of protection) |
| Enclosures | With insulating surround: IP40 With door coupling rotary handle: IP66 |
| Terminations | Tunnel terminal: IP10 Phase isolator and strip terminal: IP00 |
| Other technical data (sheet catalogue) | Temperature dependency, Derating |



With XFI earth-fault release:
 - NZM1, N1, NZM2, N2: vertical and 90° in all directions with plug-in unit
 - NZM1, N1, NZM2, N2: vertical, 90° right/left with withdrawable unit:
 - NZM3, N3: vertical, 90° right/left
 - NZM4, N4: vertical with remote operator:
 - NZM2, N(S)2, NZM3, N(S)3, NZM4, N(S)4: vertical and 90° in all directions

Circuit-breakers

| | | | |
|---|-------------|------|------------|
| Rated current = rated uninterrupted current | $I_n = I_u$ | A | 125 |
| Rated surge voltage invariability | U_{imp} | | |
| Main contacts | | V | 6000 |
| Auxiliary contacts | | V | 6000 |
| Rated operational voltage | U_e | V AC | 690 |
| Overtoltage category/pollution degree | | | III/3 |
| Rated insulation voltage | U_i | V | 690 |
| Use in unearthing supply systems | | V | ≤ 690 |

Switching capacity

| | | | |
|--|------------|-------|---|
| Rated short-circuit making capacity | I_{cm} | | |
| 240 V | I_{cm} | kA | 187 |
| 400/415 V | I_{cm} | kA | 105 |
| 440 V 50/60 Hz | I_{cm} | kA | 74 |
| 525 V 50/60 Hz | I_{cm} | kA | 40 |
| 690 V 50/60 Hz | I_c | kA | 17 |
| Rated short-circuit breaking capacity I_{cn} | I_{cn} | | |
| Icu to IEC/EN 60947 test cycle 0-t-CO | I_{cu} | kA | |
| 240 V 50/60 Hz | I_{cu} | kA | 85 |
| 400/415 V 50/60 Hz | I_{cu} | kA | 50 |
| 440 V 50/60 Hz | I_{cu} | kA | 35 |
| 525 V 50/60 Hz | I_{cu} | kA | 20 |
| 690 V 50/60 Hz | I_{cu} | kA | 10 |
| Ics to IEC/EN 60947 test cycle 0-t-CO-t-CO | I_{cs} | kA | |
| 240 V 50/60 Hz | I_{cs} | kA | 85 |
| 400/415 V 50/60 Hz | I_{cs} | kA | 50 |
| 440 V 50/60 Hz | I_{cs} | kA | 35 |
| 525 V 50/60 Hz | I_{cs} | kA | 10 |
| 690 V 50/60 Hz | I_{cs} | kA | 7.5 |
| Utilization category to IEC/EN 60947-2 | | | Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit-breaker. |
| Lifespan, mechanical (of which max. 50 % trip by shunt/undervoltage release) | Operations | A | 20000 |
| Lifespan, electrical | | | |
| AC-1 | | | |
| 400 V 50/60 Hz | Operations | | 10000 |
| 415 V 50/60 Hz | Operations | | 10000 |
| 690 V 50/60 Hz | Operations | | 7500 |
| Max. operating frequency | | Ops/h | 120 |

| | | | |
|---|-----------------|--|--------------------------------------|
| Total break time at short-circuit | ms | < 10 | |
| Terminal capacity | | | |
| Standard equipment | | Box terminal | |
| Accessories required | | NZM1-XSVS | |
| Optional accessories | | Screw connection Tunnel terminal connection on rear | |
| Round copper conductor | | | |
| Box terminal | | | |
| Solid | mm ² | 1 x (10 - 16) 2 x (6 - 16) | |
| Stranded | mm ² | 1 x (10 - 70) ³⁾ 2 x (6-25) | |
| | | ³⁾ Up to 95 mm ² can be connected depending on the cable manufacturer. | |
| Tunnel terminal | | | |
| Solid | mm ² | 1 x 16 | |
| Stranded | mm ² | 1 x (25 - 95) | |
| Bolt terminal and rear-side connection | | | |
| Direct on the switch | | | |
| Solid | mm ² | 1 x (10 - 16) 2 x (6 - 16) | |
| Stranded | mm ² | 1 x (10 - 70) ³⁾ 2 x 25 | |
| | | ³⁾ Up to 95 mm ² can be connected depending on the cable manufacturer. | |
| Al circular conductor | | | |
| Tunnel terminal | | | |
| Solid | mm ² | 1 x 16 | |
| Stranded | mm ² | 1 x (25 - 95) | |
| Bolt terminal and rear-side connection | | | |
| Direct on the switch | | | |
| Solid | mm ² | 1 x (10 - 16) 2 x (10 - 16) | |
| Stranded | mm ² | 1 x (25 - 35) 2 x (25 - 35) | |
| Cu strip (number of segments x width x segment thickness) | | | |
| Box terminal | | | |
| | min. | mm | 2 x 9 x 0.8 |
| | max. | mm | 9 x 9 x 0.8 |
| Copper busbar (width x thickness) | mm | | |
| Bolt terminal and rear-side connection | | | |
| Screw connection | | | M6 |
| Direct on the switch | | | |
| | min. | mm | 12 x 5 |
| | max. | mm | 16 x 5 |
| Control cables | | | |
| | mm ² | | 1 x (0.75 - 2.5) 2 x (0.75 - 1.5) |

Design verification as per IEC/EN 61439

| | | | |
|--|------------------|----|-------|
| Technical data for design verification | | | |
| Rated operational current for specified heat dissipation | I _n | A | 125 |
| Equipment heat dissipation, current-dependent | P _{vid} | W | 26.72 |
| Operating ambient temperature min. | | °C | -25 |
| Operating ambient temperature max. | | °C | 70 |
| IEC/EN 61439 design verification | | | |
| 10.2 Strength of materials and parts | | | |

| | | |
|--|--|--|
| 10.2.2 Corrosion resistance | | Meets the product standard's requirements. |
| 10.2.3.1 Verification of thermal stability of enclosures | | Meets the product standard's requirements. |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat | | Meets the product standard's requirements. |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects | | Meets the product standard's requirements. |
| 10.2.4 Resistance to ultra-violet (UV) radiation | | Meets the product standard's requirements. |
| 10.2.5 Lifting | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 Mechanical impact | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 Inscriptions | | Meets the product standard's requirements. |
| 10.3 Degree of protection of ASSEMBLIES | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 Clearances and creepage distances | | Meets the product standard's requirements. |
| 10.5 Protection against electric shock | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 Incorporation of switching devices and components | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 Internal electrical circuits and connections | | Is the panel builder's responsibility. |
| 10.8 Connections for external conductors | | Is the panel builder's responsibility. |
| 10.9 Insulation properties | | |
| 10.9.2 Power-frequency electric strength | | Is the panel builder's responsibility. |
| 10.9.3 Impulse withstand voltage | | Is the panel builder's responsibility. |
| 10.9.4 Testing of enclosures made of insulating material | | Is the panel builder's responsibility. |
| 10.10 Temperature rise | | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.12 Electromagnetic compatibility | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 Mechanical function | | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])

| | | |
|---|----|-----------------------------------|
| Rated permanent current I _u | A | 125 |
| Rated voltage | V | 690 - 690 |
| Rated short-circuit breaking capacity I _{cu} at 400 V, 50 Hz | kA | 50 |
| Overload release current setting | A | 100 - 125 |
| Adjustment range short-term delayed short-circuit release | A | 0 - 0 |
| Adjustment range undelayed short-circuit release | A | 750 - 1250 |
| Integrated earth fault protection | | No |
| Type of electrical connection of main circuit | | Frame clamp |
| Device construction | | Built-in device plug-in technique |
| Suitable for DIN rail (top hat rail) mounting | | No |
| DIN rail (top hat rail) mounting optional | | Yes |
| Number of auxiliary contacts as normally closed contact | | 0 |
| Number of auxiliary contacts as normally open contact | | 0 |
| Number of auxiliary contacts as change-over contact | | 0 |
| With switched-off indicator | | No |
| With integrated under voltage release | | No |
| Number of poles | | 3 |
| Position of connection for main current circuit | | Front side |
| Type of control element | | Rocker lever |
| Complete device with protection unit | | Yes |
| Motor drive integrated | | No |
| Motor drive optional | | No |
| Degree of protection (IP) | | IP20 |